

VL580 IP LARGE DISPLAY

INTRODUCTION

The VL580 IP Large Display provides highly visible message output over an Ethernet network. Text messages are created and delivered from a Valcom Application Server.

SPECIFICATIONS

Features

- Easy to read, high visibility
- Font and color options
- Power over Ethernet (PoE+) 802.3at compatible
- Display can operate as a clock or provide other message during idle periods
- Relay connection for optional equipment
- Audio line-level output connection

Dimensions / Weight

- 80.75" W x 12.13" H x 3.0" D
(205.10cm W x 30.81cm H x 7.62cm D)
- Weight: 42 lbs (19.05kg)

Nominal Power Requirements

802.3at (PoE+) Class 4
These products are intended for use with a UL Listed power source marked "Class 2" or "LPS" rated 24 Vdc, or 48 Vdc (PoE).
PoE and all interconnected ITE are intended for intra-building.

Environment

Temperature: - 20° to +50° C
Humidity: 0 - 95% non-precipitating
Suitable for outdoor exposure to direct rain (rainproof).

Maintenance

Pressure washing is acceptable, 3100 psi or less with a 25° nozzle and no closer than 10 feet.



FCC Information

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses and can radiate radio frequency energy and if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area may cause harmful interference in which case the user will be required to correct the interference at one's own expense.

IMPORTANT SAFETY INFORMATION

CONSIGNES DE SÉCURITÉ IMPORTANTES

1. Read these instructions.
Lisez ces instructions.
2. Keep these instructions.
Conservez ces instructions.
3. Heed all warnings.
Respectez tous les avertissements.
4. Follow all instructions.
Suivez toutes les instructions.
5. Do not use this apparatus near water.
Ne pas utiliser cet appareil près de l'eau.
6. Clean only with dry cloth.
Nettoyer avec un chiffon sec.
7. Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
Ne pas bloquer les ouvertures de ventilation. Installer conformément aux instructions du fabricant.
8. Do not install near any heat sources such as radiators, heat registers, stoves or other apparatus (including amplifiers) that produce heat.
Ne pas installer à proximité de sources de chaleur telles que radiateurs, registres de chaleur, poêles ou autres appareils (y compris les amplificateurs) produisant de la chaleur.
9. Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and a third grounding prong. The wide blade and the third prong are provided for your safety. If the provided plug does not fit into your outlet consult an electrician for replacement of the obsolete outlet.
Ne pas contourner le dispositif de sécurité de la fiche polarisée ou de mise à la terre. Une fiche polarisée possède deux lames dont une plus large que l'autre. Une fiche de terre a deux lames et une troisième broche de mise à la terre. La lame large et la troisième broche sont fournies pour votre sécurité. Si la fiche fournie ne rentre pas dans votre prise, veuillez consulter un électricien pour le remplacement de la prise obsolète.
10. Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles and the point where they exit from the apparatus.
11. Only use attachments/accessories specified by the manufacturer.
N'utilisez que des fixations / accessoires spécifiés par le fabricant
12. Use only with the cart, stand, tripod, bracket or table specified by the manufacturer or sold with the apparatus. When a cart is used, use caution when moving the cart/apparatus combination to avoid injury from tip-over.
Utilisez uniquement avec le chariot, stand, trépied, support ou table spécifié par le fabricant ou vendu avec l'appareil. Quand un chariot est utilisé, Soyez prudent lorsque vous déplacez l'ensemble chariot / appareil pour éviter des blessures dues au renversement.
13. Unplug this apparatus during lightning storms or when unused for a long period of time.
Débranchez cet appareil pendant les orages ou lorsqu'il n'est pas utilisé pendant une longue période de temps.
14. Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way. Such as when the power supply cord or plug is damaged, liquid has been spilled, objects have fallen into the apparatus or the apparatus has been exposed to rain or moisture and does not operate normally or has been dropped.
Confiez toute réparation à un personnel qualifié. Une réparation est nécessaire lorsque l'appareil a été endommagé de quelque façon. Par exemple lorsque le cordon d'alimentation ou la fiche est endommagé, du liquide a été renversé, si des objets sont tombés dans l'appareil ou le appareil a été exposé à la pluie ou à l'humidité et ne fonctionne pas normalement ou s'il est tombé.



- This device should not be installed beyond the building perimeter without adequate protection, such as lightning transient protection.
- Permanently discontinue power to this device if damaged in any way.
- All power to the device must be disconnected during installation or maintenance, with branch service breakers open.

CONNECTIONS

Network Connection / Power

The VL580 has one RJ-45 network connector. Connect a standard patch cable to the VL580 from an Ethernet switch supporting the Power over Ethernet specification 802.3at (PoE+). If a PoE+ switch is not available, a mid-span injector may be used to supply power to the display, or an optional Valcom 24 Vdc power adapter may be connected to the barrel connector on the circuit board (see Figure 1).

If using external power, the recommended power supply is a VP-2124D.

Relay Connection

One relay output is provided through three screw terminals labeled Normally Open (NO) and Normally Closed (NC). The center screw terminal is common to both NO and NC. The relay contacts are rated 1 amp @ 24 Vdc.

Line Out Connection

The Line Out connection provides line level output sufficient to drive up to 40 Valcom self-amplified speakers.

INSTALLATION

Mounting

The VL580 message display should be mounted with appropriate hardware (not included) for the structure to which it is attached. Use only hardware suitable for intended environmental exposure. All building codes and requirements must be followed. It is recommended to attach the mounting base into wall studs. A vial level is included to assist with leveling the mounting base. (Figure 2)

Precautions

- Mounting height should not be less than 10 feet.
- Make sure mounting method is able to support 5 times the product weight.




Figure 1. Network Connections

Status / Demo / Reset

A multifunction button is provided to display information and/or reset the VL580 configuration. The button is located on the edge of the circuit board as shown in Figure 1. The button provides different functions depending on the duration the button is pressed.

Status Mode

Press the button for approximately 1 second and release and the Status display will show the current IP Address, Power Source status and the last four digits of the MAC address.

Demo Mode

While the VL580 is in Status Mode, pressing the button again will enable Demo Mode. In this mode, the VL580 will display a scrolling sample message. Demo Mode will display for about 30 seconds then the VL580 returns to normal operation.

Reset Modes

Pressing the button continuously for greater than 10 seconds, but less than 20 seconds, will perform a soft reset on the VL580. The IP address will be reset to the factory default setting. Other configuration items will not be affected. Pressing the button continuously for greater than 20 seconds will perform a hard reset on the VL580. All of the configuration items (including the password) will be reset to factory default settings.

Setup

Information specific to your application will need to be programmed into the VL580 using a computer. The PC used for programming should be connected to the same subnet as the VL580. Setup will be done using the IP Solutions Setup Tool. Download the latest version of the free IP Solutions Setup Tool from the Valcom website at www.valcom.com/vipsetuptool

TECHNICAL ASSISTANCE

Assistance is available from the factory when problems are encountered. Call (540) 563-2000 and press 1 for Technical Support or visit our website at <http://www.valcom.com>

Valcom, Inc. equipment is not field repairable. Valcom maintains service facilities in Roanoke, VA.

Should repairs be necessary, attach a tag to the unit clearly stating company name, address, phone number, contact person, and the nature of the problem.

Send the unit to:

Valcom, Inc.
Repair and Return Dept.
5614 Hollins Road
Roanoke, VA 24019-5056

WARRANTY

Warranty information may be found on our website at www.valcom.com/warranty.




Figure 2. Mounting Diagram