

**TECHNICAL SPECIFICATION**  
**5-WATT SPEAKER**  
**MODEL V-936400**



**FEATURES:**

- 8" 5-Watt Speaker
- Combination 25, 70V Transformer
- Five Volume Settings



**DESCRIPTION:**

8-inch speaker with five volume settings. Operates on 25 or 70-volt speaker lines.

**Specifications**

**SPEAKER**

8" (20.32 cm)

**VOICE COIL**

8-ohm

**SOUND PRESSURE LEVEL**

95dB at 1 Meter on Axis with 1-Watt Input at 1 kHz

**LINE TRANSFORMER**

Combination 25/70 Volt

**TRANSFORMER TAPS**

5, 2.5, 1.25, 0.625 and 0.312 Watts

**ENVIRONMENT**

**Temperature:** -4 to +131°F (-20 to +55°C)

**Humidity:** 0-95% Non-Condensing

**DIMENSIONS AND WEIGHT**

8.0" Dia. X 2.25" D (20.3 cm x 5.7cm)

**Weight:** 1.7 lbs. (0.77 kg)

*Note: 25-Volt Speakers may be used as One-Way or Two-Way (talkback speakers). This functionality is determined by the equipment used to source audio to/from the speaker.*

**ARCHITECTS' AND ENGINEERS**

The Model V-936400 speaker shall consist of an 8" (20.32 cm) speaker with a 25/70-volt transformer.

The speaker shall be 8" (20.32 cm) in diameter. The impedance of the speaker shall be 8-ohm. The speaker shall be capable of handling 5-watts continuous power. Sound pressure level at 1 meter on axis with 1-watt input shall be 95dB. The frequency response shall be 65 Hz to 17 kHz.

The line transformer shall be capable of operating on a 25 or 70-volt line and provide 5 volume adjustments. The level adjustments shall range from .3 watts to 5 watts. Weight shall be approximately 1.7 lbs (0.77 kg).

Warranty information may be found on our website at [www.valcom.com/warranty](http://www.valcom.com/warranty).